

WEEE Number: 80133970

# **INSTRUCTION MANUAL**

LAWNLAMP

#### **TECHNICAL DATA**

MODEL	VT-7657
SKU	23353
Input Voltage	AC: 200-240V, 50Hz
IP RATING	IP65
DIMENSION	230x230x365mm
MATERIAL	Iron
HOLDER	E27(Bulb not included)
MAX WATTS	60W



IP65 O2 EXACTING WARRANTY

## **INTRODUCTION & WARRANTY**

Thank you for selecting and buying V-TAC product. V-TAC will serve you the best. Please read these instructions carefully before starting the installation and keep this manual handy for future reference. If you have any another query, please contact our dealer or local vendor from whom you have purchased the product. They are trained and ready to serve you at the best. The warranty is valid for 2 years from the date of purchase. The warranty does not apply to damage caused by incorrect installation or abnormal wear and tear. The company gives no warranty against damage to any surface due to incorrect removal and installation of the product. The products are suitable for 10-12 Hours Daily operation. Usage of product for 24 Hours a day would void the warranty. This product is warranted for manufacturing defects only.

In case of any query/issue with the product, please reach out to us at: support@v-tac.eu
For More products range, inquiry please contact our distributor or nearest dealers.
V-TAC EUROPE LTD. Bulgaria, Plovdiv 4000, bul.L.Karavelow 9B

#### **INSTRUCTIONS FOR THE LIGHT**

- 1. Please make sure to turn off the power before starting the installation.
- 2. Installation must be performed by a qualified electrician.
- 3. Proper grounding should be ensured throughout the installation.



This marking indicates that this product should not be disposed of with other household wastes.



Caution, Risk of electric shock










## **INSTALLATION DIAGRAM**



# WIRING DIAGRAM Neutral Supply can be Blue or Black Ground Supply Can be Green-yellow Live Supply Can be Red or Brown

- 1. Switch off the power before starting the installation.
- 2. Use an electric drill to punch four holes in the ground
- 3. Four explosive screws into the hole in the around
- 4. Lock the base with nuts
- 5. install the bulb into the holder
- 6. Make the wire connections with connectors.
- Connect the live wire (L) from fitting to the live wire from main power supply.
- Connect the neutral wire (N) from fitting to the neutral wire from main power supply.
- Connect the earth wire from fitting to the earth wire from main power supply.
- Please pay close attention and make sure the wires are not exposed outside when wiring connections.
- 7. Fasten the lamp body to the base with screws
- 8. Check if the installation is completed and turn on the power